

## INSTRUCTION FOR LIGHT SOURCE/CONTROL GEAR

Applied to product family and references:

<b>BOSTON 10</b>	<b>1.1145.0118</b>
<b>BOSTON 20</b>	<b>1.1146.0118</b>
<b>BOSTON 25-32</b>	<b>1.1147.0118</b>

*Replacement instruction intended for a professional.*

*Without control gear.*

*In case of doubt contact us.*


**Attention:** Before doing any works, switch off power of the mains supply or respectively of the connection lead and follow our safety precautions given in the product installation manual included in the product packaging.

- Read with care the installation manual according to product family included in the containing product.
- Uninstall the product in the reverse established order in the installation manual.
- Make sure that the product is place on a stable, even and safe environment.
- To reach the light source, first manually unscrew the front trim.
- Then, rotate the reflector and lens assembly, making it coincide with the opal polycarbonate tabs (red circles), in order to extract it, like shown in the pictures.
- Using appropriate tools, remove the opal polycarbonate that covers the light source.
- The light source is assembled by screws, unscrew them to be able to take it out.
- Collect all the removed parts of the replacement for a following reassembly.



*Pictures (as an example, the current situation may differ)*

- Once reached the light source, disconnect or desolder the positive and negative cables from circuit.
- By cooling reasons, a heat sink compound is needed between LED module and metal base. Please, be sure that the heat sink compound cover completely the LED module surface.
- In order to assemble again the product, proceed in the reverse order of this replacement instruction.



## INSTRUCCIÓN PARA FUENTE LUMINOSA/MECANISMO DE CONTROL

Aplica a la familia de producto y referencias:

<b>BOSTON 10</b>	<b>1.1145.0118</b>
<b>BOSTON 20</b>	<b>1.1146.0118</b>
<b>BOSTON 25-32</b>	<b>1.1147.0118</b>

*Instrucción de reemplazo destinada a un profesional.*

*Sin mecanismo de control.*

*En caso de duda, contacten con nosotros.*

**Atención:** Desconecte la línea de alimentación antes de realizar cualquier trabajo y siga las precauciones establecidas en el manual de instalación incluida en el embalaje del producto.

- Lea con atención el manual de instalación acorde a la familia de producto incluida en el producto continente.
- Desinstale el producto en el orden inverso al establecido en el manual de instalación.
- Preste atención que el producto esté en una base plana, estable y en un entorno seguro.
- Para alcanzar la fuente luminosa, primeramente, desenroscar manualmente el embellecedor frontal.
- Posteriormente, girar levemente el conjunto de reflector y lente haciéndolo coincidir con las pestañas del policarbonato opal (círculos rojo), para poder extraerlo, tal y como aparece en las imágenes.
- Con el uso de herramientas apropiadas, retire el policarbonato opal que cubre la fuente luminosa.
- La fuente luminosa está montada con tornillos, desatornillelos para poder retirarla.
- Recopile todas las partes retiradas por el reemplazo para un posterior reensamblaje.



*Imágenes (como ejemplo, la situación actual puede diferir)*

- Una vez alcanzada la fuente luminosa, desconectar o desoldar el cable positivo y negativo del circuito.
- Para una correcta disipación térmica, es necesario un compuesto disipador de calor entre el módulo LED y la base. Por favor, asegúrese que el componente disipador cubra toda la superficie del módulo LED.
- Realice el ensamblaje de nuevo de todos los componentes, en el orden inverso establecido en esta instrucción